

Content: 	EAN	W	lm	K	CRI	Ta (°C)	V	Hz	Dim	kg	
	8719157043311	8.5	500	6500	80	0~+40	220-240	50/60	ND	0.7	
	Circuit Breaker										
	B16	45PCS									
C16		75PCS									

Dimension: 	*Dimension in mm											
	Inrush current						8.5W					
	Driver						BY-Z2410E					
	Inrush current I _{peak} (A)						1.06A		Input voltage 230V			
Inrush current T _{width} (µs)						3000µs		Input voltage 230V, measured at 50% I _{peak}				

1 Remove the diffuser.

2 Body installation.

3 Electrical connection.

4 Attach diffuser.

Power Cord Dimensions Ø4-Ø8
1.0mm²-1.5mm²
Wire Type: H05RN-F / H07RN-F

Warning note

Suitable for mounting on normally flammable surface Green LED indicator indicates battery charging mode Safety and performance are in accordance with EN55015, EN61347, EN60598-1, EN60598-2-22, EN61000-3-2, EN61000-3-3 Suitable for indoor use, wall mounted if the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard. The battery is non-replaceable.
Installation: The installation shall be done by a qualified person.

TESTING:

The emergency lighting must be inspected and tested regularly in accordance with local Codes of practice, **Note:** tests should be carried out during day time for safety reasons. The testing should be done by a qualified person, in an dry environment. Move the plastic diffuser, press the test button to simulate failure of mains power, the Emergency light should be on and driven by battery.

The minimum recommended test schedule is as follows: Charge the battery for 36 hours after installation to ensure the battery is full and then observe if the light can discharge for 3 hours.

- Daily check that charge indicator LED is working.
- Monthly interrupt power for a short period to check LED lights.
- Semiannually check 1 hour duration.
- At the end of year and subsequent year. Check 3 hour duration: batteries must be replaced when they can no longer support 3 hour operation.
- Complete record sheet on installation and retain file.
- Update file with ongoing test records for inspection by fire officer or other daily authorized person.

Both the LED light source and control gear equipped in this product cannot be replaced.

EN The luminaire shall be installed and maintained by a qualified electrician, in accordance with the national regulations in each country. The luminaire contains no replaceable parts. In case of the luminaire is damaged, it shall be exclusively replaced by the manufacturer or authorized dealer. Keep the operating manual for later use. The manufacturer is not responsible for the incorrect use and assembly of this product.

NL De armatuur dient te worden geïnstalleerd en onderhouden door een erkend installateur, in overeenstemming met de nationale regelgeving in het betreffende land. De armatuur bevat geen vervangbare onderdelen. Indien de armatuur is beschadigd dient deze enkel te worden vervangen door de fabrikant of door een erkende dealer. Bewaar de handleiding voor later gebruik. De fabrikant is niet verantwoordelijk voor onjuist gebruik en/of installatie van dit product.

DE Die Leuchte muss von einem qualifizierten Elektriker gemäß den nationalen Vorschriften in jedem Land installiert und gewartet werden. Die Leuchte enthält keine austauschbaren Teile. Falls die Leuchte beschädigt ist, wird sie ausschließlich durch den Hersteller oder den autorisierten Händler ersetzt. Bewahren Sie die Bedienungsanleitung für spätere Verwendung auf. Der Hersteller ist nicht verantwortlich für die unsachgemäße Verwendung und Montage dieses Produktes.

FR Le luminaire doit être installé et entretenu par un électricien qualifié, conformément à la réglementation nationale de chaque pays. Le luminaire ne contient pas de pièces remplaçables. Dans le cas où le luminaire est endommagé, il doit être remplacé exclusivement par le fabricant ou le revendeur agréé. Conservez le mode d'emploi pour une utilisation ultérieure. Le fabricant n'est pas responsable de l'utilisation et du montage incorrects de ce produit.

IT L'apparecchio deve essere installato e mantenuto da un elettricista qualificato seguendo le normative nazionali di riferimento. L'apparecchio non contiene parti sostituibili. In caso di rottura sarà sostituito esclusivamente dal produttore o da un rivenditore autorizzato. Conservate il manuale di installazione per eventuali utilizzi successivi. Il produttore non è responsabile per l'utilizzo ed il montaggio non corretto di tale apparecchio.

ES La luminaria debe de ser instalada y mantenida por un electricista cualificado, siguiendo las regulaciones nacionales de cada país. La luminaria contiene partes no reemplazables. En el caso de que la luminaria sea dañada, deberá ser reemplazada exclusivamente por el fabricante o distribuidor autorizado. Guarde el manual para usos posteriores. El fabricante no es responsable por el uso e instalación incorrecta de este producto.